

This Page Is Inserted by IFW Operations
and is not a part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,
please do not report the images to the
Image Problems Mailbox.**

(12) UK Patent Application (19) GB (11) 2 140 558 A

(43) Application published 28 Nov 1984

(21) Application No 8333956

(22) Date of filing 21 Dec 1983

(30) Priority data

(31) 8236058 (32) 22 Dec 1982 (33) GB

(71) Applicant
McMichael Limited (United Kingdom),
Sefton Park, Bells Hill, Stoke Poges, Slough SL2 4HD

(72) Inventor
Colin Peter Clare

(74) Agent and/or Address for Service
J. D. Dolwin,
Central Patent Department (Wembley Office),
The General Electric Company plc, Hirst Research Centre,
Wembley, Middlesex HA9 7PP

(51) INT CL³
G01S 3/80

(52) Domestic classification
G1G 1G2 9S RC

(56) Documents cited
GB 1544447 GB 1350031
GB 1544277 EP A1 0031750
GB 1395599

(58) Field of search
G1G

(54) Acoustic direction finding systems

(57) In a hydrophone system in which the direction of acoustic waves impinging on an array of hydrophones is determined from measurements of the periods between successive zero-crossings of waves detected by the two hydrophones of each of several different pairs of the hydrophones, allowance is made for the fact that the start and finish of such a period may be due to zero-crossings of different waves. In the embodiment shown the hydrophones H_0 - H_4 are arranged in two linear groups disposed at right angles to one another, with unequal spacing between adjacent pairs of hydrophones in each group. In another embodiment (Figure 4, not shown) the hydrophone array consists of five hydrophones disposed at the corners of a regular pentagon.




Fig. 1.





Fig. 4.



2/3




Fig. 2.*Fig. 3.*

Fig. 5.

SPECIFICATION

Acoustic direction finding systems

- 5 This invention relates to acoustic direction finding systems and to methods of operating same. More particularly, but not exclusively, the invention is concerned with hydrophone systems. 5
- In a known form of hydrophone system, a plurality of hydrophones are equally spaced in a cruciform array, and the direction of waves impinging on the array is determined in dependence upon the periods between zero-crossings of the waves detected by different pairs of the hydrophones.
- 10 An object of the present invention is to provide an improved hydrophone system. 10
- According to one aspect of the present invention, a method of operating an acoustic direction finding system which comprises an array of a plurality of spaced electro-acoustic transducers disposed in a plane to determine the direction of waves impinging on the array includes the steps of measuring the periods between successive instants of zero-crossings of waves detected by different pairs of transducers,
- 15 comparing such periods in respect of different pairs of transducers, the ratio of the distances between the appropriate pairs of transducers being non-integral, and checking which comparisons correspond to the times for a wavefront to pass between the appropriate pairs of transducers being in the said ratio after due allowance has been made for the fact that at least one of said periods may be determined by transducers responding to different zero-crossings. 15
- 20 According to another aspect of the present invention, an acoustic direction finding system comprises an array of at least five electro-acoustic transducers disposed in two groups each having three transducers, one of which may be common to both groups, along two orthogonal lines in a plane, the ratio of the spacings between different pairs of transducers in each of the two groups being non-integral, and means responsive to periods between instants of zero-crossing of waves detected by said different pairs of transducers in the
- 25 two groups, after allowance for the fact that said period may be determined by transducers responsive to different zero-crossings, for determining the quadrant in said plane emanating from the array in which lies the source of waves impinging thereon. 25
- Preferably the ratio of the spacings of said different pairs of transducers in each group is 1.5.
- According to yet another aspect of the invention, an acoustic direction finding system comprises an array
- 30 of at least three electro-acoustic transducers which are disposed in a plane so that no three of the transducers are in a straight line and means for comparing the periods between instants of zero-crossing of waves detected by different pairs of said transducers and from such comparison and the disposition of the transducers verifying which periods are in respect of zero-crossings of the same wave and means for determining from said verified periods the direction in said plane of the source of waves impinging on the
- 35 array. 35
- In a preferred construction of the array, there are five transducers disposed at the corners of a regular pentagon.
- Examples of hydrophone systems and methods of operating same in accordance with the invention will now be described with reference to the five figures of the accompanying drawings in which:
- 40 *Figure 1* shows the first hydrophone system diagrammatically, 40
- Figures 2 and 3* are perspective views of two alternative hydrophone arrays for use with the first system,
- Figure 4* shows the second system diagrammatically, and
- Figure 5* is a perspective view of the hydrophone array of the second system.
- Referring to *Figure 1* of the accompanying drawings, the first hydrophone system comprises an array of
- 45 five hydrophones, H_0 , H_1 , H_2 , H_3 and H_4 , each of which is a piezo-electric transducer such as the Bruel and Kjaer type 8103. The two groups of hydrophones H_0 , H_1 and H_2 and H_0 , H_3 and H_4 are disposed respectively in two orthogonal lines which can conveniently be considered the Y and X axes respectively of a cartesian reference system having its origin at the location of the hydrophone H_0 . The two hydrophones H_1 and H_3 are spaced a distance d from the hydrophone H_0 while the pairs of hydrophones H_1 , H_2 and H_3 , H_4 are spaced a
- 50 distance $3d/2$ apart. 50
- Each of the five hydrophones H_0 and H_4 has associated electronic circuits 2 (of known form) for determining the instants of zero-crossing of acoustic waves impinging on the hydrophone and each such determination is signalled to a digital computer 1 over a path 3. It may be mentioned here that the hydrophone system can only be operated to obtain the direction (from the hydrophone array) of such a
- 55 source of waves if the wavelength of these waves is not less than d . 55
- During use of the hydrophone system, the individual hydrophones H_0 to H_4 respond to acoustic waves from a remote source in turn and the computer 1 is arranged to measure the delay between successive zero-crossings as follows:-

60	Delay	Between	60
	t_1	H_0 and H_1	
	t_2	H_0 and H_3	
	t_3	H_1 and H_2	
65	t_4	H_3 and H_4	65

The computer 1 is also arranged to measure the period τ between successive zero-crossings of waves impinging on the hydrophone array. This measurement may conveniently be effected in respect of one hydrophone, say the hydrophone H_0 , but, although this period should be the same for all the hydrophones of the array, it may be preferable to derive a value for τ as the mean time between zero-crossings of each of the 5 hydrophones H_0 to H_4 .

The hydrophones H_0 to H_4 are, in fact, carried on a solid member (not shown but the surface of which lies generally in the X-Y plane of Figure 1) so that waves can only reach the hydrophone array from directions above the X-Y plane of the drawing.

From the measurements of t_1 to t_4 and τ , the computer 1 is arranged to determine in which of the octants A, 10 B, C or D lies the source of waves impinging on the hydrophone array as will now be described. For each of these octants there is a predetermined relationship between the measured times t_1 and t_3 and another predetermined relationship between the times t_2 and t_4 due to the geometry of the arrangement. In all cases there are however two possible relationships depending upon whether or not there is an intervening zero-crossing of the incoming waves between the hydrophones H_1 and H_2 or between the hydrophones H_3 15 and H_4 as appropriate. It can be shown that these relationships are as follows:-

Octant A		Octant B	
20	$t_3 = \begin{cases} 3t_1/2 \\ \text{or} \\ 3t_1/2 - \tau \end{cases}$	$t_3 = \begin{cases} (3t_1 + \tau)/2 \\ \text{or} \\ (3t_1 - \tau)/2 \end{cases}$	20
25	$t_4 = \begin{cases} 3t_2/2 \\ \text{or} \\ 3t_2/2 - \tau \end{cases}$	$t_4 = \begin{cases} 3t_2/2 \\ \text{or} \\ 3t_2/2 - \tau \end{cases}$	25
Octant D		Octant C	
30	$t_3 = \begin{cases} 3t_1/2 \\ \text{or} \\ 3t_1/2 - \tau \end{cases}$	$t_3 = \begin{cases} (3t_1 + \tau)/2 \\ \text{or} \\ (3t_1 - \tau)/2 \end{cases}$	30
35	$t_4 = \begin{cases} (3t_2 + \tau)/2 \\ \text{or} \\ (3t_2 - \tau)/2 \end{cases}$	$t_4 = \begin{cases} (3t_1 + \tau)/2 \\ \text{or} \\ (3t_1 - \tau)/2 \end{cases}$	35

It will be noted that these relationships are different for each of the four octants. Thus, if t_3 is equal to either 40 $3t_1/2$ or $3t_1/2 - \tau$ it follows that the wave source must be in either octant A or D while if t_4 is equal to $3t_2/2$ or $3t_2/2 - \tau$ the source must be in either octant A or B. It is therefore strictly only necessary for the computer 1 to effect the calculations and comparisons just referred to in order to ascertain the appropriate octant but, in practice, it may be more satisfactory for the computer 1 to effect all the calculations and comparisons listed above and then to determine the octant in which the wave source lies on a 'best fit' basis.

45 It may be mentioned that, if the hydrophone array had been responsive to waves from either side of the X-Y plane, the relationships just discussed could be utilised to determine the quadrant about the Z axis (in effect two octants one on either side of the X-Y plane) in which the wave source lies.

Reverting to the four octant case, it can be shown that, if the direction of wave source, measured from the hydrophone array, makes angles θ_a and θ_b to the X and Y axes in the X-Z and Y-Z planes respectively, these 50 angles are given by the following expressions:-

Octant A		Octant B	
55	$\theta_a = \begin{cases} 180 - \cos^{-1}(t_2/t_d) \\ 180 - \cos^{-1}(3t_2/3t_d) \\ 180 - \cos^{-1}(2(t_4 + \tau)/3t_d) \end{cases}$	$\theta_a = \begin{cases} 180 - \cos^{-1}(t_2/t_d) \\ 180 - \cos^{-1}(2t_2/3t_d) \\ 180 - \cos^{-1}(2(t_4 + \tau)/3t_d) \end{cases}$	55
60	$\theta_b = \begin{cases} 180 - \cos^{-1}(t_1/t_d) \\ 180 - \cos^{-1}(2t_1/3t_d) \\ 180 - \cos^{-1}(2(t_3 + \tau)/3t_d) \end{cases}$	$\theta_b = \begin{cases} \cos^{-1}(\tau - t_1)/t_d \\ \cos^{-1}(2(\tau - t_3)/3t_d) \\ \cos^{-1}(2(2\tau - t_3)/3t_d) \end{cases}$	60

	Octant D		Octant C	
5	$\theta_\alpha = \begin{bmatrix} \cos^{-1} ((\tau - t_2)/t_d) \\ \cos^{-1} (2(\tau - t_4)/3t_d) \\ \cos^{-1} (2(2\tau - t_4)/3t_d) \end{bmatrix}$	$\theta_\alpha = \begin{bmatrix} \cos^{-1} ((\tau - t_2)/t_d) \\ \cos^{-1} (2(\tau - t_4)/3t_d) \\ \cos^{-1} (2(2\tau - t_4)/3t_d) \end{bmatrix}$	5	
10	$\theta_\beta = \begin{bmatrix} 180 - \cos^{-1}(t_1/t_d) \\ 180 - \cos^{-1}(2t_3/3t_d) \\ 180 - \cos^{-1}(2(t_3 + \tau)/3t_d) \end{bmatrix}$	$\theta_\beta = \begin{bmatrix} \cos^{-1} (\frac{\tau - t_1}{t_d}) \\ \cos^{-1}(2(\tau - t_3)/3t_d) \\ \cos^{-1}(2(2\tau - t_3)/3t_d) \end{bmatrix}$	10	

where t_d is the time taken for a wavefront to traverse the distance d in its direction of propagation.

Having first established the octant in which the wave source lies (as previously described), the computer 1 proceeds to calculate the value of each of the angles θ_α and θ_β using the one of the alternative formulae which is likely to give the most accurate answer and a value of t_d equal to the time taken for a wavefront to travel the distance d in water, due correction to the velocity of sound in water being given for the temperature, pressure and salinity of the water.

In practice, it may be convenient for the array to have four additional hydrophones with the total of nine hydrophones disposed in a symmetrical cruciform array centred on the hydrophone H_0 , such an arrangement providing some redundant information but at the same time improving the overall performance of the system. Furthermore the spacing of the three hydrophones in each arm of the array may be changed, without affecting the basis of the determinations and calculations previously described, so that the spacing between the central hydrophone (corresponding to H_0) and the adjacent hydrophone (corresponding to H_1 or H_3) in each arm is 1.5 times the spacing between the two outer hydrophones of each arm. Such a hydrophone array is shown in Figure 2 of the accompanying drawings.

In the cruciform array of hydrophones, some hydrophones may be subject to acoustic shadowing by adjacent hydrophones. This can be reduced by having an array of 'T' configuration which is otherwise utilised in the same way as previously described. Such an array is shown in Figure 3 of the drawings and comprises two like modules 4 and 5 each having five sub-miniature hydrophones 6 mounted on a steelplate 7, the distance D between the centres of the two modules 4 and 5 being not more than a few wavelengths at the frequency of use.

Referring now to Figures 4 and 5 of the accompanying drawings, the second form of hydrophone system to be described comprises five hydrophones H_5 to H_9 which are located at the corners of a regular pentagon. The hydrophones H_5 to H_9 are mounted on a steel plate 8. Again the instants of zero-crossings of waves impinging on the hydrophones H_5 to H_9 are detected by circuits 9 and signalled to a digital computer 10.

In this embodiment of the invention, the computer 10 is arranged to store information identifying the times of occurrence (relative to an arbitrary reference) of at least the first, second and third zero-crossings detected by each of the five hydrophones H_5 to H_9 after the commencement of a computation sequence to ascertain the direction of a source of waves impinging on the array. From this information, the computer 10 calculates and stores the periods between each of the first zero-crossings detected by each of the hydrophones H_5 to H_9 and each of the first, second and third zero-crossings detected by each of the other hydrophones. One example of the periods so calculated is that between the first zero-crossing detected by the hydrophone H_5 and the first zero-crossing detected by the hydrophone H_7 , while another example is the period between the first zero-crossing detected by the hydrophone H_6 and the third zero-crossing detected by the hydrophone H_9 .

It will be appreciated from the geometry of the hydrophone array that the time taken for any given wavefront to pass from hydrophone H_5 to hydrophone H_9 will always be in a fixed ratio of $\sin 54^\circ$ (approximately 1.618) to the time taken for the same wavefront to pass from the hydrophone H_6 to the hydrophone H_7 . There are, in fact, a total of ten such ratios for different pairs of hydrophones and, to ascertain the direction in which the source lies, the computer 10 compares successive pairs of said periods to determine which of them (after due allowance has been made for any intervening zero-crossings by virtue of knowledge of the wave period τ) are in accordance with one of the fixed ratios. This involves a total of ninety calculations.

Under ideal conditions, ten of the calculations just referred to should give the appropriate fixed ratio, thereby verifying that the time-difference measurements involved are in respect of the same wavefront, although in practice it is not uncommon for a lesser number of such verifications to be effected.

Once the time-difference measurement in respect of a pair of the hydrophones H_5 to H_9 has been verified, the direction of the source is calculated by the computer from the verified measurement. For example, assuming the time difference t between the first zero-crossing detected by the hydrophone H_6 and the first zero-crossing detected by the hydrophone H_9 has been verified in respect of waves arriving in the direction of the arrow A and remembering that the distance between the hydrophones H_6 and H_9 is $1.618d$, where d is the distance between adjacent hydrophones, it follows that the direction of the source is at an angle α to a datum line 12 through the hydrophone array as given by the following expression:

$$\sin \alpha = ct/1.62d$$

where c is the velocity of sound in water (after correction as in the first example described above).

- 5 It will be appreciated that waves emanating from the direction $180-\alpha$ will give the same time difference measurement and, to remove this ambiguity and give a unique solution it is necessary for a similar calculation to be effected in respect of another verified time-difference measurement. 5

The construction of hydrophone array described above with reference to figures 4 and 5 has the advantage that, unlike a linear array, it enables the hydrophone system to operate at wavelengths significantly less than the minimum physical spacing of the hydrophone. This is an important consideration if the spacing is 10 comparable to the actual size of each hydrophone so that the spacing cannot be further reduced to extend the bandwidth. 10

When operating any of the hydrophone systems described above in an environment having a poor signal to noise ratio, it is necessary first to verify that a "good" signal is present. A number of threshold tests for 15 achieving this have previously been proposed. For example the computer may be arranged, in response to zero-crossings detected by one of the hydrophones of the array, to determine the magnitude of the quantity $\tau - \bar{\tau}$, where τ has the meaning previously ascribed herein and $\bar{\tau}$ is the mean value of τ taken over a large number of zero-crossings (preferably weighted to favour more recent measurements), the computer being 20 arranged only to perform the direction-finding calculations if this magnitude has less than a predetermined value. 20

CLAIMS

1. A method of operating an acoustic direction finding system which comprises an array of 25 electro-acoustic transducers disposed in a plane to determine the direction of waves impinging on the array including the steps of measuring the periods between successive instants of zero-crossings of waves detected by different pairs of transducers, comparing such periods in respect of different pairs of transducers, the ratio of the distances between the two transducers of such pairs being non-integral, and checking which comparisons correspond to the times for a wavefront to pass between the appropriate pairs 30 of transducers being in the said ratio after due allowance has been made for the fact that at least one of said periods may be determined by transducers responding to different zero-crossings. 30
2. A method according to Claim 1 wherein said array of transducers comprises at least five transducers disposed in two groups each having three transducers, one of which may be common to both groups, along two orthogonal lines in the plane and the results of said checking determining the quadrant in said plane 35 emanating from the array in which lies the source of waves impinging thereon. 35
3. A method according to Claim 1 wherein said array of transducers comprises at least three transducers disposed so that no three of the transducers are in a straight line and the method includes the further step of determining from a measured period which has been verified by being checked as aforesaid the direction in said plane in which lies the source of waves impinging on the array.
4. An acoustic direction finding system comprising an array of at least five electro-acoustic transducers 40 disposed in two groups each having three transducers, one of which may be common to both groups, along two orthogonal lines in a plane, the ratio of the spacings between different pairs of transducers in each of the two groups being non-integral, and means responsive to periods between instants of zero-crossing of waves detected by said different pairs of transducers in the two groups, after allowance for the fact that said period 45 may be determined by transducers responsive to different zero-crossings, for determining the quadrant in said plane emanating from the array in which lies the source of waves impinging thereon. 45
5. A direction finding system according to Claim 4 wherein the ratio of the spacings of said different pairs of transducers is 1.5.
6. An acoustic direction-finding system comprising an array of at least three electro-acoustic transducers 50 which are disposed in a plane so that no three of the transducers are in a straight line and means for comparing the periods between instants of zero-crossing of waves detected by different pairs of said transducers and from such comparison and the disposition of the transducers verifying which periods are in respect of zero-crossings of the same wave and means for determining from said verified periods the direction in said plane of the source of waves impinging on the array.
7. A direction finding system according to claim 6 wherein the array has five transducers disposed at the 55 corners of a regular pentagon. 55
8. A hydrophone system according to any one of Claims 4 to 7.
9. A hydrophone system substantially as hereinbefore described with reference to Figure 1, Figure 2 or Figure 3 of the accompanying drawings.
10. A hydrophone system substantially as hereinbefore described with reference to Figures 4 and 5 of the 60 accompanying drawings. 60